



139.95 EUR

incl. 19% VAT, plus [shipping](#)

- Intel WiFi, Intel WiDi !
- Dual Gigabit LAN !
- Gigabyte Features !
- NVMe M.2 slot !



- Supports 7th/ 6th Generation Intel® Core™ Processors
- Dual Channel Non-ECC Unbuffered DDR4, 2 DIMMs
- Intel® USB 3.1 Gen 1 with USB Type-C™
- Intel® Optane™ Memory Ready
- Ultra-Fast M.2 with PCIe Gen3 x4 & SATA interface
- ALC1220 120dB SNR HD Audio with Smart Headphone Amp
- 802.11ac Dual Band 867Mbps wireless supports MU-MIMO and BT4.2
- Dual Intel® GbE LAN with cFosSpeed Internet Accelerator Software
- Smart Fan 5 features Multiple Temperature Sensors and Hybrid Fan Headers
- Ultra Durable™ Metal Shielding over PCIe Slots
- GIGABYTE UEFI DualBIOS™
- APP Center Including Cloud Station™ Utility

|                  |   |
|------------------|---|
| CPU              | <ol style="list-style-type: none"><li>1. Support for 7th and 6th generation Intel® Core™ i7 processors/Intel® Core™ i5 processors/Intel® Core™ i3 processors/Intel® Pentium® processors/Intel® Celeron® processors in the LGA1151 package</li><li>2. L3 cache varies with CPU</li></ol> <p>(Please refer "CPU Support List" for more information.)</p>  |
| Chipset          | <ol style="list-style-type: none"><li>1. Intel® H270 Express Chipset</li></ol>  |
| Memory           | <ol style="list-style-type: none"><li>1. 2 x DDR4 DIMM sockets supporting up to 32 GB of system memory * Due to a Windows 32-bit operating system limitation, when more than 4 GB of physical memory is installed, the actual memory size displayed will be less than the size of the physical memory installed.</li><li>2. Dual channel memory architecture</li><li>3. Support for DDR4 2400* / 2133 MHz memory modules</li><li>4. Support for ECC Un-buffered DIMM 1Rx8/2Rx8 memory modules (operate in non-ECC mode)</li><li>5. Support for non-ECC Un-buffered DIMM 1Rx8/2Rx8/1Rx16 memory modules</li><li>6. Support for Extreme Memory Profile (XMP) memory modules * To support 2400 MHz or XMP memory, you must install a 7th generation processor.</li></ol> <p>(Please refer "Memory Support List" for more information.)</p> |
| Onboard Graphics | <p>Integrated Graphics Processor:</p> <ol style="list-style-type: none"><li>1. 1 x DVI-D port, supporting a maximum resolution of 1920x1200@60Hz</li><li>2. 2 x HDMI ports, supporting a maximum resolution of 4096x2160@24Hz or 2560x1600@60Hz<br/>* Support for HDMI 1.4 version.</li><li>3. Support for up to 3 displays at the same time<br/>* To set up a triple-display configuration, you must connect a D-Sub monitor using a DVI-to-D-Sub adapter.</li><li>4. Maximum shared memory of 1 GB</li></ol>  |
| Audio            | <ol style="list-style-type: none"><li>1. Realtek® ALC1220 codec</li><li>2. High Definition Audio</li><li>3. 2/4/5.1/7.1-channel</li><li>4. Support for S/PDIF Out</li></ol>   |
| LAN              | <ol style="list-style-type: none"><li>1. 2 x Intel® GbE LAN chips (10/100/1000 Mbit)</li></ol>  |

---

|                                  |  |
|----------------------------------|--|
| Wireless<br>Communication module | <ol style="list-style-type: none"><li>1. Wi-Fi 802.11 a/b/g/n/ac, supporting 2.4/5 GHz Dual-Band</li><li>2. BLUETOOTH 4.2, 4.1, BLE, 4.0, 3.0, 2.1+EDR</li><li>3. Support for 11ac wireless standard and up to 867 Mbps data rate<br/>* Actual data rate may vary depending on environment and equipment.</li></ol>  |
| Expansion Slots                  | <ol style="list-style-type: none"><li>1. 1 x PCI Express x16 slot, running at x16<br/>(The PCIEX16 slot conforms to PCI Express 3.0 standard.)</li><li>2. 1 x M.2 Socket 1 connector for the wireless communication module (M2_WIFI)</li></ol> <p>Chipset:</p>   |
| Storage Interface                | <ol style="list-style-type: none"><li>1. 1 x M.2 connector on the back of the motherboard (Socket 3, M key, type 2260/2280 SATA and PCIe x4/x2 SSD support)</li><li>2. 6 x SATA 6Gb/s connectors</li><li>3. Support for RAID 0, RAID 1, RAID 5, and RAID 10</li></ol> <p>Chipset:</p>  |
| USB                              | <ol style="list-style-type: none"><li>1. 2 x USB 2.0/1.1 ports available through the internal USB header</li><li>2. 6 x USB 3.1 Gen 1 ports (4 ports on the back panel, 2 ports available through the internal USB header)</li><li>3. 1 x USB Type-C™ port on the back panel, with USB 3.1 Gen 1 support</li></ol>   |
| Internal I/O Connectors          | <ol style="list-style-type: none"><li>1. 1 x 24-pin ATX main power connector</li><li>2. 1 x 4-pin ATX 12V power connector</li><li>3. 6 x SATA 6Gb/s connectors</li><li>4. 1 x M.2 Socket 3 connector on the back of the motherboard</li><li>5. 1 x CPU fan header</li><li>6. 1 x system fan header</li><li>7. 1 x front panel header</li><li>8. 1 x front panel audio header</li><li>9. 1 x USB 3.1 Gen 1 header</li><li>10. 1 x USB 2.0/1.1 header</li><li>11. 1 x S/PDIF Out header</li><li>12. 1 x Clear CMOS jumper</li><li>13. 1 x chassis intrusion header</li></ol> |

|                       |  |
|-----------------------|--|
|                       | <ol style="list-style-type: none"><li>1. 1 x PS/2 keyboard/mouse port</li><li>2. 2 x HDMI ports</li><li>3. 2 x SMA antenna connectors (2T2R)</li><li>4. 1 x DVI-D port</li></ol>   |
| Back Panel Connectors | <ol style="list-style-type: none"><li>5. 4 x USB 3.1 Gen 1 ports</li><li>6. 1 x USB Type-C™ port, with USB 3.1 Gen 1 support</li><li>7. 2 x RJ-45 ports</li><li>8. 1 x optical S/PDIF Out connector</li><li>9. 5 x audio jacks (Center/Subwoofer Speaker Out, Rear Speaker Out, Line In, Line Out, Mic In)</li></ol>   |
| I/O Controller        | <ol style="list-style-type: none"><li>1. iTE® I/O Controller Chip</li></ol>  |
| H/W Monitoring        | <ol style="list-style-type: none"><li>1. System voltage detection</li><li>2. CPU/System temperature detection</li><li>3. CPU/System fan speed detection</li><li>4. CPU/System fan speed control<br/>* Whether the fan speed control function is supported will depend on the cooler you install.</li></ol>   |
| BIOS                  | <ol style="list-style-type: none"><li>1. 2 x 128Mbit flash</li><li>2. Use of licensed AMI UEFI BIOS</li><li>3. Support for DualBIOS™</li><li>4. PnP 1.0a, DMI 2.7, WfM 2.0, SM BIOS 2.7, ACPI 5.0</li></ol>  |
| Unique Features       | <ol style="list-style-type: none"><li>1. Support for APP Center * Available applications in APP Center may vary by motherboard model. Supported functions of each application may also vary depending on motherboard specifications. 3D OSD @BIOS Ambient LED AutoGreen BIOS Setup Color Temperature Cloud Station EasyTune Easy RAID Fast Boot Game Boost ON/OFF Charge Platform Power Management Smart Backup Smart Keyboard Smart TimeLock System Information Viewer USB Blocker V-Tuner</li><li>2. Support for Q-Flash</li><li>3. Support for Smart Switch</li><li>4. Support for Xpress Install</li></ol> |

|                  |  |
|------------------|--|
| Bundle Software  | <ol style="list-style-type: none"><li>1. Norton® Internet Security (OEM version)</li><li>2. Intel® Wireless Display</li><li>3. Intel® Optane™ Memory Ready</li><li>4. cFosSpeed</li></ol>  |
| Operating System | <ol style="list-style-type: none"><li>1. Windows® 10 64-bit (for 7th Generation Intel® Processors)</li><li>2. Windows® 10 64-bit / Windows® 8.1 64-bit / Windows® 7 32-bit / 64-bits (for 6th Generation Intel® Processors) * Please download the "Windows USB Installation Tool" from GIGABYTE's website and install it before installing Windows 7.</li></ol>                                      |
| Form Factor      | <ol style="list-style-type: none"><li>1. Mini-ITX Form Factor; 17.0cm x 17.0cm</li></ol>   |
| Remark           | <ol style="list-style-type: none"><li>1. Due to different Linux support condition provided by chipset vendors, please download Linux driver from chipset vendors' website or 3rd party website.</li><li>2. Most hardware/software vendors may no longer offer drivers to support Win9X/ME/2000/XP. If drivers are available from the vendors, we will update them on the GIGABYTE website.</li></ol> |